050 plus Operations Manual

for Android 2017.2





Contents



Chapter 08 Setting list 2 P.58 P.58 · · · Section 05 : Adjust the volume P.59 · · · Section 06 : Change the call volume P.60 ··· Section 07 : Change the background image and color of the button on the keypad P.62···Section08 : Change notification settings / Display information list P.63 · · · Section 09 : Calling from other dialer Chapter09 Control Menu O P.64 P.65 · · · Section01 :Log in to the Control Menu +] Chapter 10 Change the registered information **P.66** P.67 · · · Section 01 : Change the address, phone number, or mail address P.68 · · · Section 02 : Change the credit card information for payment P.69...Section03 : Initial setting when changing the device Ą Chapter11 Password P.70 P.71 ··· · Section 01 : If you forgot your password. P.72 · · · Section 02 : Change your password Chapter 12 Details of call charges P.73 P.74 · · · Section 01 : Confirm the bill details P.76 · · · Section 02 : Confirm the call details Chapter13 Test Call P.77 Chapter14 Recommend to a friend P.79 Chapter 15 Result of Cost-Saving P.81 P.82 · · · Section 01 : Cost-Saving of each call P.83 · · · Section 02 : Cost-Saving of monthly P.84 · · · Section 03 : Select a price play P.85 · · · Section 04 : Reconfiguration when upgrading Chapter16 Network Monitor P.86

P.92···Section01 : Change the availability of international calls

- P.94 · · · Section 02 : Termination
- P.95 · · · Section 03 : Use in multiple devices
- P.96 · · · Section 04 : Use Bluetooth device

Chapter17 Supplement

P.98 · · · Section 06 : FAQ (Introduction of Web site)

P.91

P.97 ··· Section 05: Consent of the notification at Application start-up.



Thank you for selecting "050 plus" the app for cost-saving call charges.

This document is to guide a variety of information beginning with the basic operation.

If you have any questions, please contact according to the following pattern.


Inquiries about "050 plus"			
How to apply	"050 plus" Easily Apply http://www.ntt.com/en/personal/services/phone/050plus/step.html		
Contact by E-mail	"050 plus" WEB site http://support.ntt.com/050plus/inquiry/search Depending on the time of day and congestion situation of the query, the answer might be the next day. Please acknowledge it beforehand.		
Contact by Phone	From mobile phone or fixed telephone (Before the contract) Toll-free 0120-506-506 Reception Time 10:00 - 19:00 (Except for the sunday,holiday,year-end and the New Year)		
Notice of maintenance	Information about the maintenance of "050 plus" http://support.ntt.com/maintenance/service/78		

**No part of this document may be reproduced without the permission of the NTT Communications Corporation. **The contents of this document may be changed without prior notice.

 $\ensuremath{\ll}\xspace$ Wi-Fi is the brand name that has been authenticated by Wi-Fi Alliance ,

indicating that interoperability between wireless LAN equipment.






Section 01 Chapter 01


Names and Functions of the Home screen

A name and function of each part in the "keypad" screen"



1	"Message" Use the 050 plus apps, and send text messages. <u>> Learn more</u>
2	"Contacts" Select a contact from you address book > Learn more
3	"Recents" History of the call <u>> Learn more</u>
4	"Number display field" Displays the number you enter
5	"Button to add a contact" Add to the contact number you entered
6	"Keypad" Input the number you tapped
7	"Mobile Call" Make a call by mobile phone network to the displayed number
8	"IP Call" Make a call by the internet access to the displayed number Start the "Photo Talk" Service by press and hold this button <u>> Learn more</u>
9	"Delete key" Erase one digit number in a short tap All numbers will be erased in a long tap
10	"Settings" Check and change the configuration of the "050 plus" application > Learn more






Basic Operation of an Android phone

Using "Menu key" on an Android phone








Section 01-3 Chapter 01

Basic Operation of Android terminals

Confirm a status of app



6







Make a call

Input the phone number of the call at "Keypad"





 \odot Close



App will be terminated completely when you tap "Close"

at Android menu

후 📶 🧯 11:03 AM . Favorites Contacts Keypad Recents 2 ABC 3 DEF 1 5 6 MNO **4** GHI 7 PORS **9** wxyz 8 TUV 0 × # -0- \odot Close Settings Android Menu





Make a call from "Contacts"

Select a contact from your address book





Address book will appear when you tap "Contacts"





Tap a contact you want to call

%If there are multiple phone numbers to a contact, you need to specify the number again



Tap "IP Call" **C IP Call** after confirming that the number of the "Keypad" screen is right (then a call is started)





Make a call from "Favorites"

You can easily make a call if a contact is registered to "Favorites"






2.

Open the "Contacts" screen by tapping the contacts button. Tap the "Favorites" button. Favorites

A call is started by simply tapping the one in the list.





Confirm the free call number of "050"

Distinguish the free 050 number











Take a photo or Select a photo

Start the "Photo Talk" Service




Tap and hold "IP Phone" button

If you are in a call




Swipe "Action button" and Tap"photo" button















Edit a photo

Write a message to send photo



Take Photo

"Preview"




Display "Edit Menu" and Edit



機能紹介		
1	A Krypad	Show "Keypad"
2	Delete	Change the color of the character font
3	Dorne	Finish "Edit Menu"
4	C	Rotate a photo





Make a call

Make a call with the photo




機能紹介					
1	•	You can see pictures which you send or received in the Call by swipe.			






History of the use of "Photo Talk"

Browse the history of the use of the "Photo Talk" Service









٩.


Λ

Emily's

Message

Start message

Select destination and send a message





Enter text, tap Send button. Send Message is sent.

* Number of characters that can be sent in one message is 500 characters. (It does not matter full width/half width)




Section Chapter 04

Description of message screen ① Message screen


The following operation buttons are available in message screen.





Description of message screen ② Member list screen

<u>The member list shows users whom you can make free calls to.</u> <u>The following operation buttons are available in the member list screen.</u>







How to use the message function 1 Send message





2.

1-1: To select from the member list for sending/receiving Select the destination
 1-2: To specify destination by entering 050 number
 Enter the phone number in the 050 number input area, turn the member's radio button
 on.
 1-3: To search phone book and select destination
 Enter name or 050 number in search field to narrow the search, select destination, and turn radio button
 on.
 Tap Start button Start on the navigation bar Starts message.
 1-1: To search phone book
 Tap Start button Start
 Tap Start button Start

+857

You can send a message form history screen.









How to use the message function ② Group message

You can create a group with more than one party to exchange messages.




Others

- · Phone number is not registered in the contacts are displayed as "guest".
- · Block members be included in the group, you can message.




How to use the message function 3 Inviting members

From the member list, select multiple members.




 Others Group members are up to 20 people, including your number You can not add more members



How to use the message function (4) Find members

You can find members who are participating in group message from the mark on the top-right of the navigation bar.

🚰 🦉 🖫 🖬 👘	🚰 🖀 🐨 🕼 🕼 🕼	* 📠 🖏 🎲 78% 🖬 9:28
John Smith,Taro Yamada(2) 🛛 🔻 🗾	John Smith,Taro Yamada(2) 🛛 📥	Member (5)
	Invite Exit Delete Members	Hanako Sato
Taro Yamada	Group Settings Taro Yamada has joined Taro Yamada	Ichiro Sato
How's going? 2013/10/17 11:30	How's going? 2013/10/17	Jiro Oda
2013/10/17 11:31 I'm O.K.	2013/10/17 I'm O.K. 11:31	John Smith
Taro Yamada	Taro Yamada	
Would you like to go to l 2013/10/17	Would you like to go to I unch? 2013/10/17 11:32	Guest
2013/10/17 O.K. 1 11:33	2013/10/17 O.K. 11:33	
Send	Send	
 ▲ = ⊕ 	♠ = ₽	
Message	Message 2	Participants



can do so by pressing Exit button.






Section Chapter 04

How to use the message function (5) Change a group name

You can edit group name.








4.





How to use the message function 6 To make call

Tap destination's icon or phone number in the message to make a call.






1-1: To make call form icon

Tap destination's icon.

1-2: To make call to phone number in the message Tap phone number in the message.



Pop-up screen appears, and tap the "IP Call" button.








How to use the message function 🔿 Add a contact

Add a contact by tapping the icon







How to use the message function (8) Send message during incoming call

Incoming call, you can reply to choose the message



When you switched to the incoming screen there is an incoming call, tap the button **o**



1.


Tap the Reply with Message



Tap the selected message.

■Other

- •The message can be edited and registration from the configuration.
- ·If there is an incoming call from the 050 plus other than, you can not reply with message.



How to use the message function 9 Edit "Fixed phrase"

You can edit the message of "Fixed phrase"

1	Fixed phrase 17:13 Fixed phrase Ide	2	3
Message Setting	Fixed Phrase	Message Edit	
1.Select "Fixed phrase"2.Tap the Editand3.Tap the OKImage: Select		g"	

■Other

- •To return to "Massage Setting" if you tap Done
- •Check from "Fixed phrase" if you want to see the message you have edited.


OK



Section
03-10
Chapter 04

How to use the message function 10 Notification area

Message notification is shown in notification area.



New message can be alerted by the Notification area, Popup, Banner. Tap to go to message screen.

Other


- •The application can receive notification in the background state / not running.
- •Notification settings for 050 plus is not notified in the case of "OFF". The initial setting is "ON".
- •Notification pop-up setting for 050 plus does not pop up in the case of "OFF". The initial setting is "ON".



Section 03-11 Chapter 04

How to use the message function 1 Delete history

Delete message



· Caution

•You can not undo the deleted messages.



How to use the message function 12 Block function

You can use block function to disable sending to/receiving from the specified members.



34

Section

Chapter 04


1



Section 03-13 Chapter 04

How to use the message function (3) Unblock

You can unblock the member you are blocking.






Section 03-14 Chapter 04

How to use the message function 14 Message Setting

From Settings, you can view/change various information.


	🌈 📽 🍹 🥮 11:20 Settings		🍺 📽 🐩 🥌 11:21 App Settings		🌈 🐞 🏆 Message Settings	11:21	
	Control Menu		Notify caller's phone number Notification notify		Message		1
	App Settings		Ringtone and Vibration		Notifications		2
	Cost-saving		Sound and vibration settings		Pop-up Notifications		3
	Test Call		Call settings				
			Master volume		Block List		4
	Recommend to Friend		Advanced settings		Fixed phrase		5
	Support		Message			_	
	Information list		Message Settings				
	About 050 plus		Button availability				
	for new/re-installed App		Use Background image				
	Initialize		Background image change				
	My 050 Number		Mobile Call				
	♠ ≡ ⊕		▲ ▲ = ⊕		★ ★ =	ð	
	Settings		App Settings		Message Setting	3	
Des	cription of functions f	for me	essage settings				
Des 1	cription of functions f Message	Set "	essage settings 'Function of Message" ce en off, you can not use the				
Des 1		Set" ※Who	'Function of Message" ce	Message	function.		
Des 1 2		Set " ※Who Set " •ON: •OFF ※Tur	'Function of Message" ce en off, you can not use the	Message DN" or " e reception Start the	e function. OFF" on of the message is n app, it displays a mes	sage	
1	Message	Set " %Who Set " •ON: •OFF %Tur notific	Function of Message" ce en off, you can not use the Push information" cell to "O 050 plus is not running, the Reception is not notified. So n off the set the notification	Message DN" or " e reception Start the n function	e function. OFF" on of the message is n app, it displays a mes	sage	
1	Message	Set " *Who Set " •ON: •OFF *Tur notific Set " •ON: •ON: •OFF	'Function of Message" ce en off, you can not use the Push information" cell to "O 050 plus is not running, the Reception is not notified. S n off the set the notification cation,	Message DN" or " e reception Start the n function OFF" e pop-up Start the	e function. OFF" on of the message is n app, it displays a mes n of 050 plus in Andro appears. app, it displays a mes	sage bid OS, ssage	
1	Message Notifications	Set " *Who Set " •ON: •OFF *Turn notific Set " •ON: •OFF *Turn	'Function of Message" ce en off, you can not use the Push information" cell to "O 050 plus is not running, the :Reception is not notified. S n off the set the notification cation, Pop-up" cell to "ON" or "O 050 plus is not running, the :The pop-up not appears. S	Message DN" or " e reception Start the n function OFF" e pop-up Start the	e function. OFF" on of the message is n app, it displays a mes n of 050 plus in Andro appears. app, it displays a mes	sage bid OS, ssage	





Use in multiple devices

- •Can not be used the message function, set to "Non-notification"
- •Via message dedicated server: Messages that after three months or more, remove from the server.







÷., **Open Contacts**

Creating and editing of group from the list of contacts



💼 🚮		🛇 🚺 1:31 PM
	<u>,</u>	
Message C	ontacts k	2 Recents
-		
List	Group	Favorites
や		
A Tar Mob	o Yamada ^{ile}	
	"Contacts	5"

Contacts






2.

The list of groups will appear where you tap at "Contacts" screen

you tap Group

icon




Case of selecttion the group already created





Create a new group

Organize your contacts into groups








Edit the group

Edit or delete the group








3.

Android Menu appears




About setup menu				
1	Add group	Create a new group		
2	Edit group	Change a name or change members of the group		
3	Delete group	Delete the group		
4	Change color	Select the color of the group		
5	Add contact destination	Add new contacts into the group		

 $\$ If you synchronize the contacts on the internet , part of editing work may not work properly







Add a contact to "Favorite"

You can easily make a call if a contact is registered to "Favorite"



1.

Tap a member to register to "Favorite" at "Contacts" screen



3.

If tapping a star , the color of the star will change from 🖈 to Then that contact will be registered

If the member having multiple phone numbers , select some of those





Delete a contact from favorite




Tap the contact button 1. Tap the Favorite button


3.

2. If tapping a star , the color of the star will change from 🙀 to 📩





The contact will be removed from "Favorite" ***Member itself is not deleted from "Contacts"**















Confirm Voicemail

Listen and Delete the voicemail received

Messages are stored under the following conditions Max 20 messages Up to 90 second per message Will be erased automatically after 168 hours (7 days)








Set the answering message

Set the answering message of original by your own voice








Call time setting if you do not answer the call

If you do not answer the phone during an incoming call, you can set the time until connected to the Voice Mail Center



※ If you when you can call, you do not want to connect to the voice mail center, Please set the "−" to "call time".








Contents of setting list

<u>Check and change configuration of "050 plus" can be done from the</u> <u>"Setting list"</u>









Contents of Setting list

G 《 11 ≁ 100 20. Settings	Ab	out "Setting List"	
Control Menu App Settings	1	Control Menu	Confirm and change your information (address,password,such as)
Cost-saving Test Call	2	App Settings	Caller ID, incoming calls, cos savings and other settings
Network monitor (Manual) Recommend to Friend	3	Cost-saving	Confirm the number of calls per month, prices, cost savings
Support Information list	4	Test Call	Test experience "050 plus" for free
About 050 plus for new/re-installed App Initialize	5	Network monitor (Manual)	Check the network condition
My 050 Number Version	6	Recommend to Friend	Recommend "050 plus" to a friend
"Setting list"	7	Support	Confirm the information of "050 plus" maintenance
	8	Information list	Information list of notifications received in the past
	9	About 050 plus	Link to "050 plus" WEB site
	10	Initialize	Initial settings for model changes ,for reinstalling "050 plus"
	11	My 050 Number	Show your 050 phone number
	12	Version	Confirm "050 plus" version





Configure of App

Configuration of the behavior of App



ON-OFF can be set for items below

- "Notify caller's Phone number"
- "Ringtone Melody"
- "Call settings"

1.

2.

- "Advanced Settings"
- "Message Settings"
- "Background image change"
- "Mobile Call"
- "Enable Call from other Apps"
- "Push infomation"
- "Photo talk"
- "My pocket"
- "Cost-saving"
- "Talk quality alarm"
- "Application starts automatically"

- -> Notify or Not'
- -> Change the ringtone
- -> Adjust the volume
- -> Do not change usually
- > Do not change usually
- -> Set the Message function
- -> Change the image of the keypad
- -> Available or Not
- -> Add or Not
- -> Receive notification or Not
- -> active or inactive
- -> active or inactive
- -> Show or Not
- -> Sounds or Not
- -> Start or Not








Confirm own phone number

Confirm own phone number at "Setting list"









Auto Start

ON-OFF setting of start "050 plus" automatically when the phone's power is ON








Adjust the volume

Adjust the volume of the voice of the people you hear







Tap "Master volume"



Can not be changed manually in the case of on-the "Automatic Gain Control" of the "Microphone".

If it turn "Off" of the "Automatic Gain Control", you can operating the slider.

- •When you slide to the right, your voice will be heard to the other larger.
- •When you slide to the left, your voice will be heard to the other smaller.

Operating the "Earpiece volume".


- •When you slide to the right, the other party's voice be heard larger.
- •When you slide to the left, the other party's voice be heard smaller.





Change the ringtone

Select a ringtone from the music




1.	Tap "App Setting" in Settings
2.	Tap "Sound and vibration settings"
З.	Tap "Ringtone settings"
4.	Tap "Use Android ringtone"or "Use music track",select music you want to set the ringtone
5	Select the radio button at last




Section 07-1 Chapter 08

Change the background image and color of the button on the keypad

Change the background image of the keypad









Change the background image and color of the button on the keypad (2)

Adjust the size of image, change the color and transparency of the button



Go to "Background image change" first

Please tap the "color setup" ※ The color adjustment is complete, tap OK

Please tap "Transparency" *Configuration is complete, tap the OK

3.

2.

1.

Please touch the "trimming", you can adjust the size of the image

4.

5.

Select "fit to loger side" or "fit to shorter side", adjust the alignment of the image


Tap "Save" at last






Change notification settings / Display information list

•About change notification settings and display information list



< About change notification settings >



<About display information list>



Tap "Information list"







Calling from other dialer

You can set when you call from other dialer

Mapp Settings	🐨 📶 🌆 10:11	🔁 🕂 🗃 🚍 ሹ 🦶 🕼 후 🗉 Advanced settings	di 🖅 21:10	👩 🕸 🛅 🤤 🚮 🤍 🎊 Advanced settings	हे 📶 🌠 21:11
Notify caller's phone number		Ear piece		Ear piece	
Notification	notify				
Ringtone and Vibration		Speaker		Speaker	
Sound and vibration settings		If you select the check, it will reduce the echo.(recommended)		Setting	
Call settings		Reduce voice data delay			
Master volume		Sent voice data	~	Default	
Advanced settings Message Message Settings		Received voice data	~	Forcible display	
		If you select the check, it will rec delay in voice by regulating the when the network is congested. commended)	duce the voice data	Forcible non-display	
Button availability		tting call from other dialer		Setting call from other di	aier
Use Background image Background image change App Settings		Default		Default	
		Setting the display of 050 plus ic make a call from other dialer.	con when	Setting the display of 050 j make a call from other dia	plus icon when ler.
App Setting	5	Advanced Setting	JS	Settings	S



2.

3.

Tap "Advanced Setting"

Set from "Setting call from other dialer" %Please set in the "Default" normal


Please change the settings in the following cases

Pop-up for selecting the 050 plus does not appear

- -> "Forcible display"
- Pop-up is displayed twice
- -> "Forcible non-display"








Log in to the Control Menu

Registered information can be changed by logging in to the "Control Menu"







Section 01 Chapter 10

Change own Address, Phone number ,E-mail adress

	🚰 🛛 😤 📶 🛑 11:03 AM	📻 👘 📋 11:03 AM
1	Control Menu	Change your info
	Personal info Change your info	Contractor name Input mode screen will appear when you tap the item you want to change
	Change sword	First name The changes are determined to tap "Done
	Chang red Charge info	Family name Contractor name
	Bill	Address, Mobile phone number
	Call details Option setting	2 ostal code Addres search
	Option setting	Address
	Supplement	
	International call	Lot number (Option)
	"Control Menu"	e.g. building (Option)
	This screen can be seen by	Mobile phone number
	selecting "Control Menu" at "Settings" screen > Learn More	Mail address
		Mail address
		Inquiry ID
		And a second secon
	By 55 miles	Needed to make inquriy
L		Commit
		Your Information

1.

2.

+

Tap "Your Information" after logging in "Control Menu"

Tap "Commit" after confirming the changes %Item with gray character is unmodifiable

Section 02 Chapter 10

Change the credit card infomartion for payment 😤 📶 🥚 11:03 AM GP 후 💵 📔 11:03 AM **Control Menu** Change credit card info Personal info Credit card number Change your info 2 No hyphen card number Change password 05 2012 Term of validity Change credit card info Security code Charge info **Bill details** Commit Call details Option setting Option set Supplement International call "Control Menu" **Change Card Info** [What Security code is] This screen can be seen by 3-digit or 4-digit numbers appear in the upper right corner selecting "Control Menu" at of the back of the card in the signature area "Settings" screen Sometimes visible on the surface of card > Learn More Front of the card Back of the card 1234 5678 9012 3 56 789 34 567 1234 5678 901 Security code **%**If the card has changed in the update and reissue will also change security code **%**If security code is not visible, please ask your credit card company



2.

- Tap "Change Card Info" after logging in "Control Menu"
- Tap "Commit" after confirming the changes



Section 03 Chapter 10

Initial setting when changing the mobile phone

Even if mobile phone model changes or re-install the application, "050 plus" is available





2.

Tap "Initialization of 050 plus" at "Setting list" screen

Tap "Execute initialization" after you enter 050 number and password








If you forgat your password

Re-issue the password


3.



Tap "Re-issue password" after entering "050 number" and "E-mail address", then New password will be send by e-mail

* "050 number" is entered automatically if initialization is already done





Change your password 😤 📶 📒 11:03 AM Б, 💵 📔 11:03 AM **Control Menu** Change password Personal info 2 Current password Change your info Current password Change password New Password Change credit d info New 6 digits of alphanumeric Password Charge info **Re-entry** Bill ails Call de Commit Option setting Option setting Supplement International call "Control Menu" "Change password" This screen can be seen by selecting "Control Menu" at "Settings" screen > Learn More 1 11 0 3 6



2.

Tap "Change password" at "Control Menu"

Tap "Commit" after entering "Current password" and "New password"

> If you forgat password..








Confirm the bill details

The total and breakdown of the past three month can be see at "Bill details"



Tap "Bill details" after logging in "Control Menu"





Section 02-1 Chapter 12

Confirm the call details

The total and breakdown of the past four month can be see at "Call details"



Tap "Call details" after logging in "Control Menu"

📻 रू 📶 🥚 11:03 AM Control Menu	call detail	
Personal info		Total of
Change your info	通話利用明細	call details
Change password		
Change credit card info	2 通話利用明細	(合計)
narge info	通話利用明細	(内訳)
Bill details	Breakdown of	周去4ヶ月で
Call details	call details	
Option setting Option set		での通話
Internation Consol a consol a consol		
"Control Menu"	"Call de	tails"
This screen can be seen by selecting "Control Menu" at "Settings" screen <u>> Learn More</u>		








Select "Total of call details" or "Breakdown of call details"

Total of call details



1 Tap a month to see

②"通話数"	Number of calls
"通話時間"	Talk time
"通話料金"	The call charges

Total of call details

Breakdown of call details




③ Tap a month to see


④"日付"	Date
"電話番号"	Phone number
"利用時刻"	Time
"通話料"	The call charges

- (5) Tap to see (6)
- ⑥ "通話年月日" Number of calls
 "通話開始時刻" Time to start
 "通話先電話番号" Phone number
 "通話先地域" Area to call
 "通話時間" Talk time
 "通話種別" Type
 "サービス表示" Display the survice
 "料金" The call charges

76







Test Call

Try the app for free






Tap "Test Call" at "Control Menu" screen


You can experience the call of "050 plus" when you tap "Call"





Recommend to a friend

Tell your own 050 number and app's URL to a friend by e-mail




Tap "Recommend to a friend" at "Control Menu" screen


2.

Choose whether describing your 050 number or not



Mail application will launch in a state that subject and content have been described %Please come to recommend because it is free calls between apps








Section


Cost-Saving of each

<u>After the end of the call,</u> <u>call charges and cost reduction amount and talk time ,</u> <u>such as the sum of them will be displayed</u>





1	Estimated call charges of "050 plus"
2	Estimated call charges of Mobile Phone
3	Difference of the amount above 2 (means Cost-Saving)
4	The total monthly cost savings
5	Description of cost savings (http://050plus.com/profit/index.html)






Cost-Saving of monthly





83





Select mobile phone company 10.00


Select plans that is the basis to calculate Cost-Saving




Tap company's name at "Your rate plan" field



Cost savings can be calculated by selecting mobile phone company that you use





Reconfigure when you upgrade the app

After upgrading from version 2.x.x. you must decide on a single rate plan when you first start the app



1. Select a company and a rate plan you use



Tap "OK" after confirming the plan you use

This is an operation of only once when you upgrade from 2.xx This Screen does not appear unless you select a plan







You can check the network condition automatically.



The following screen appears when you updates app or initialize app. Tap "Yes" .

Network monitor		
Will you monitor th condition while dia		
Yes	No	



If the connection state is unstable, I will display the 2 to display the status bar at the bottom of.


<Status list>

	Status Bar	Description
1	050 plus is Available	Network condition is stable
2	Retwork connection is unstable	Network condition is unstable
3	Disconnect	State can not call
4	Network unavailable	Not connected to the network
5	Connectiong	Trying to connect to the network

Section

Chapter 16







Check the network condition automatically Check the network condition automatically



If the connection state becomes unstable during a call, display with [Connection is unstable] on the screen.








Check the network condition manually

You can check the connection status of the network manually.



1.


Tap "Network Monitor (Manual)" at "Settings".

2.

Check the network status is started.

results	Description
Stable	Network condition is stable
Unstable	Network condition is unstable
Disconnected	Not connected network (State can not call)
Now monitoring	Monitoring network condition
Monitoring terminated	Network monitoring terminated





Setting Network Monitor

Setting of Network Monitor.

	7		 A call is possible. App Settings 			Advanced settings	భు "ము ≁యం 20:25
1	Control Menu		Notify caller's phone number	1		If you select the check, echo.(recommended)	it will reduce the
4	App Settings		Notification	notify		Reduce voice data de	lay
	Cost-saving		Ringtone and Vibration			Sent voice data	×
	Cost-saving		Sound and vibration set	tings		Received voice d	ata 🔽
	Test Call		Call settings			If you select the check, voice by regulating the	it will reduce the delay in
	Network monitor (Manual)		2 Master volume			network is congested.(r	
	Recommend to Friend		Advanced settings			Setting call from othe	r dialer
	Support		Message			D	efault
			Message			Setting the display of 0 call from other dialer.	50 plus icon when make a
	Information list		Button availability		Network monitor		
	About 050 plus		Use Background image		3	Automatic monite	or 🔽
	for new/re-installed App		Background image cha	nge	_	Connection quali	ty alarm 📃
	Initialize	1	Mobile Call			An alarm will be issued unstable while talking	when the network go
	Settings		App Settings	3		Advance	ed settings

Tap "AppSettings" at "Settings".



1.

Tap "Advanced settings".

3.

<Automatice Monitor>

Turn on if you want to check the connection status in automatic.

<Quality Alarm>

When the connection state becomes unstable during a call and notify you by alarm. Default setting is off.









International call

Change the availability of international call








Tap "Request change" after confirming current setting





International call





4

Tap "Continue to Confirmation Screen" after entering information, The contracter name, The 050IP phone number, The phone number, The contract mail address, Select "available" or "unavailable".







International call


🖻 🕼 🤗 📶 📕 4:19PM	4	🖻 🕼 🤶 👘 💼 3:39PM
NTT Communications	_	NTT Communications
Overseas calling Japanese		質問が送信されました
Please be sure to read the following when requesting changes to your overseas		質問を受け付けました。 (The question was received.) ご利用いただきましてありがとうございます。 (Thank you for using.)
calling settings. The contractor name *		
Contact ID		
tex: YFF1234567890123) The 0501P phone number *		・トップ(Top) Powered by RightNow
iec 65012543676)		Copyright@2012 NTT Communications
The phone number *		▲ ▷ C ×
(ex: 05012345678) The contract mail address *		"International call"
ies: example@nti com.com) 'International' call The request of the use setting *		
- 🛛		
Next	3.	Tap "Next" after entering information The contracter name Contract ID
・トップ(Top) Powered by A		The 050IP phone number
Copyright @2012 NTT Communications		The phone number The contract mail address
▲ ► C ×		Select "available" or "unavailable"
"Internatinal call"		
	4.	The request will be recieved





Termination

The procedure to terminate the contract





Tap "Termination" at "Control Menu" screen

If you agree descriptions of screen, check "I agree to above" and tap "Next"

After answering a questionnaire , the procedure will be complete with tapping "terminate"






Use in multiple devices

- 1. Can not be used simultaneously by multiple terminal
- 2. If make a 050 call to the other terminal during a call at one terminal, voice guidance to explain during a call will be played
 ※If Voice mail is set , a call will be connected to the voice mail center
- 3. In order to make a call certainly at the terminal, the app of all other terminals must to be closed, then restart the app in the terminal





Use Bluetooth devices

1. Conditions of availability

Android OS version	2.2 or higher
Bluetooth version	2.0+EDR or higher
Profile	HSP(not HFP)

<About "profile"> HSP (HeadSet Profile) Connect with Headset devices


HFP (Hands Free Profile) Call with hands free Call making operation is possible, such as incoming and outgoing call

Some devices on this condition may be unavailable Please read each operation manual before using the device

- 2. By following reasons, a talk might be difficult because of sound is not clear •Compatibility or Distance between devices is not good
 - •The battery level is low
 - •Radio interference, such as Wi-Fi
- 3. With Bluetooth devices, call making operation is impossible
- 4. Ringtone sound is depend on A2DP profile during Bluetooth being conected

A2DP	Sounds from speaker and bluetooth
not A2DP	Sounds from speaker

- 5. Devices with A2DP profile
 - Please turn off the Bluetooth connection, if you couldn't change device from Bluetooth device during a call
 - •Please try to reconnect the Bluetooth device , if there is no sounds from music app after talking by Bluetooth device



You can change the settings at a later time. \approx [Settings] \Rightarrow [App Setting] [Push information]

Would you like?

• App Version.

Yes

Initialization Status.

For more information, please refer to the "Change notification settings" of Chapter07–Section08.

No





Frequently Asked Question

If there is any question, please refer following web site



